


BoostVolt


Charging—Now!



Easy installation without grid extension at the AC connection



Adjustable battery capacity enables more than ultra-fast charging



Display Additional revenue from advertisement



Charging from 20% to 80% in 15 minutes

Model	BV100A	BV200L
Battery Capacity	100kWh	200kWh
Charging Socket Output	2xCCS2	2xCCS2
Max DC Charge Output Power	90 kW-DC 2x45kW-DC	180 kW-DC 2x90kW-DC
AC Charge Input	40kW-AC (3phase) 0%-100%: ~2.5h	40kW-AC (3phase) 0%-100%: ~5h
e-Generator AC Output	Optional	
Cooling	Air Cooling	Liquid Cooling
Battery Type	LFP	
Depth of Discharge (DOD%)	90% Recommended	
Control Panel	10" Touchscreen	
Advertising Display	55" Screen	
Charging Communication Protocol	OCCP 1.6/2.0.1	
On/Off Confirmation	RFID	
IP Protection Level	IP54	
Operating Temperature	Charge 0°C to 50°C Discharge -20°C to 55°C	
Warranty	2 Years	
Cycle Life	6000	

Model	BV300L	BV400L
Battery Capacity	300kWh	400kWh
Charging Socket Output	2xCCS2	2xCCS2
Max DC Charge Output Power	240 kW-DC 2x120kW-DC	240 kW-DC 2x120kW-DC
AC Charge Input	60kW-AC (3phase) 0%-100%: ~5h	60kW-AC (3phase) 0%-100%: ~7h
e-Generator AC Output (220V AC socket output)	Optional	
Cooling	Liquid Cooling	
Battery Type	LFP	
Depth of Discharge (DOD%)	90% Recommended	
Control Panel	10" Touchscreen	
Advertising Display	55" Screen	
Charging Communication Protocol	OCCP 1.6/2.0.1	
On/Off Confirmation	RFID	
IP Protection Level	IP54	
Operating Temperature	Charge 0°C to 50°C Discharge -20°C to 55°C	
Warranty	2 Years	
Cycle Life	6000	